

SPECIFICATIONS

Frequency: 630 - 960 MHz (According to local regulations)
Channel Frequencies: 192 PLL selectable channels per frequency band
RF Output: 10mw
Frequency Stability: ± 0.005%
Frequency Deviation: ± 48KHz
S/N Ratio: > 102db
Audio Frequency: 50Hz - 15KHz
Dynamic Range: > +110db
Controls: Power On/Off Frequency and AF Level set
LCD Information: Frequency and battery status
Switching: Programmable touch switch and LED indicator
Power Supply: 2 x AA Batteries giving more than 9 hours use
Output: 24 Volts Phantom Power
Connection: 3Pin XLR
Finish: Black
Dimensions: **Length** 125mm (4.93") **Width** 115mm (4.53") **Diameter** 40mm (1.58")
Weight: 394g (13oz)
Accessories: Floor stand



Programming options

Program mode (Press number of times for selection required)	Description	Option 1 (Press Once)	Option 2 (Press Twice)
1	Switch Type	Momentary	Latching
2	Switch Action	PTT (Normally Off)	PTM (Normally On)
3	Activation Tone	Off	On

Switch operating Instructions

- 1) Apply power with switch pressed.
- 2) Unit gives regular flash for 2 seconds on LED to show set up mode entered.
- 3) Press switch the number of times of the programming mode you wish to check or change. The interval between key presses must be less than 1 second.
- 4) After the mode has been selected the LED will flash the number of times of the option currently set.
- 5) Press the switch the number of times of the option required. The interval between key presses must be less than 1 second.
- 6) The LED will flash the number of times of the option already set.
- 7) The unit then returns to stage 2, ready for setting more options.
- 8) The unit will return to normal operation after 5 seconds if the key is not pressed.